



PATENT

Agent's Docket No. 12742-US

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

In re Application of)

SEIBERT, Michael)

Serial No: 10/042,237)

Art Unit: 2643

Filed: 11-January-2002)

Examiner:

For: **DOUBLE-TALK AND PATH CHANGE DETECTION USING A
MATRIX OF CORRELATION COEFFICIENTS**

RECEIVED
MAR 11 2002
Technology Center 2600

March 4, 2002

Commissioner of Patent and Trademarks

Washington, D.C. 20231

TRANSMITTAL LETTER

Sir:

Submitted herewith are the following documents:

- Transmittal Letter (in duplicate)
- Certified copy of Priority Document (British Application No. 0100674.1)

Respectfully submitted,


BY: 

Richard J. Mitchell
Reg. No. 34,519
Agent of Record

MARKS & CLERK
P. O. Box 957, Station B
Ottawa, Ontario Canada K1P 5S7 (613) 236-9561

ETH

This Page Blank (uspto)



TRANSMITTAL LETTER
(General - Patent Pending)

Docket No.
12742-US

In Re Application Of:

Michael SEIBERT

Serial No.
10/042,237

Filing Date
January 11, 2002

Examiner

Group Art Unit
2643

Title:

DOUBLE-TALK AND PATH CHANGE DETECTION USING A MATRIX OF CORRELATION
COEFFICIENTS

TO THE COMMISSIONER OF PATENTS AND TRADEMARKS:

Transmitted herewith is:

Certified Copy of British Priority Document 0100674.1, Filed January 11, 2001

RECEIVED
MAR 11 2002
Technology Center 2600

in the above identified application.

- ☒ No additional fee is required.
- ☐ A check in the amount of _____ is attached.
- ☐ The Commissioner is hereby authorized to charge and credit Deposit Account No. _____ as described below. A duplicate copy of this sheet is enclosed.
- ☐ Charge the amount of _____
- ☐ Credit any overpayment.
- ☐ Charge any additional fee required.


Signature

Dated: 4-March-2002

Richard J. Mitchell 34,519
MARKS & CLERK
P. O. Box 957, Station B
Ottawa, Ontario Canada K1P 5S7
Tel: (613) 236-9561

I certify that this document and fee is being deposited
on _____ with the U.S. Postal Service as
first class mail under 37 C.F.R. 1.8 and is addressed to the
Commissioner of Patents and Trademarks, Washington,
D.C. 20231.

Signature of Person Mailing Correspondence

Typed or Printed Name of Person Mailing Correspondence

CC:

This Page Blank (uspto)



The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

RECEIVED
MAR 11 2002
Technology Center 2600

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name in which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., p.l.c. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.


Signed

Dated

- 7 FEB 2002

CERTIFIED COPY OF
PRIORITY DOCUMENT

This Page Blank (uspro)



11JAN01 E597071-2 D01063
F01/7700 0.00-0100674.1

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

The Patent Office

Cardiff Road
Newport
South Wales
NP10 8QQ

1. Your reference

RL.P51450GB

01/11 JAN 2001

11 JAN 2001

0100674.1

2. Patent application number

(The Patent Office will fill in this part)

3. Full name, address and postcode of the or of each applicant (*underline all surnames*)

Mitel Corporation
P.O. Box 13089
350 Legget Drive
Kanata, Ontario
Canada
K2K 2W7

Patents ADP number (*if you know it*)

If the applicant is a corporate body, give the country/state of its incorporation

CANADA

607630006

4. Title of the invention

Double-Talk and Path Change Detection Using a Matrix of Correlation Coefficients

5. Name of your agent (*if you have one*)

Marks & Clerk

"Address for service" in the United Kingdom to which all correspondence should be sent (*including the postcode*)

Marks & Clerk
4220 Nash Court
Oxford Business Park South
Oxford
OX4 2RU

Patents ADP number (*if you know it*)

727 1125 001

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (*if you know it*) the or each application number

Country

Priority application number
(*if you know it*)

Date of filing
(*day / month / year*)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing
(*day / month / year*)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (*Answer 'Yes' if:*

Yes

- a) any applicant named in part 3 is not an inventor, or
 - b) there is an inventor who is not named as an applicant, or
 - c) any named applicant is a corporate body.
- See note (d))

Patents Form 1/77.

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form (none)

Description 11

Claim(s) 2

Abstract 1

Drawing(s) 2 *+ 2 fl*

10. If you are also filing any of the following, state how many against each item.

Priority documents (none)

Translations of priority documents (none)

Statement of inventorship and right to grant of a patent (*Patents Form 7/77*) (none)

Request for preliminary examination and search (*Patents Form 9/77*) 1

Request for substantive examination (*Patents Form 10/77*) (none)

Any other documents (none)
(*please specify*)

11. I/We request the grant of a patent on the basis of this application.

Signature *Marks & Clerk* Date 10 Jan 2001
Marks & Clerk

12. Name and daytime telephone number of person to contact in the United Kingdom Dr. Robert Lind 01865 397900

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- a) If you need help to fill in this form or you have any questions, please contact the Patent Office on 08459 500505.
- b) Write your answers in capital letters using black ink or you may type them.
- c) If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- d) If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- e) Once you have filled in the form you must remember to sign and date it.
- f) For details of the fee and ways to pay please contact the Patent Office.

Double-Talk and Path Change Detection Using A Matrix of Correlation Coefficients

BACKGROUND OF THE INVENTION

Field of Invention

This invention relates to a method of detecting double-talk and path changes in echo
5 cancellation systems. Echo cancellation is used extensively in telecommunications applications to recondition a wide variety of signals, such as speech, data transmission, and video.

Brief Description of the Prior Art

The search for an effective echo cancellation procedure has produced several different
10 approaches with varying degrees of complexity, cost, and performance. A traditional approach to echo cancellation uses an adaptive filter of length L , where L equals the number of samples necessary to extend to just beyond the duration of the echo. Typically, the adaptive filters contain either 512 or 1024 taps. At the standard telephone bit rate of 8000 samples per second, this provides the ability to adapt to echo paths as long as 64 ms
15 and 128 ms, respectively.

The computational requirements of an adaptive filter are proportional to L for the popular LMS (Least Mean Squares) class of algorithms, and proportional to L^2 or higher for algorithms such as RLS (Recursive Least Squares). More robust algorithms (like RLS) have greatly improved convergence characteristics over LMS methods, but the L^2
20 computational load makes them impractical with current technology. For this reason, the LMS algorithm (and its variants) tends to remain the algorithm of choice for echo cancellation.

Practical echo cancellation devices must provide some means of avoiding divergence from double-talk. The double-talk condition arises when there is simultaneous
25 transmission of signals from both sides of the echo canceller due to the presence of near-end speech in addition to the echo. Under such circumstances, the return echo path signal, S_{IN} (see Figure 1), contains both return echo from the echo source signal, and a double-talk signal. The presence of a double-talk signal will prevent an LMS-based echo canceller from converging on the correct echo path. It will also cause a pre-converged

echo canceller to diverge to unpredictable states. Following divergence, the echo canceller will no longer cancel the echo, and must reconverge to the correct solution. Such behaviour is highly unacceptable, and is to be avoided in actual devices. Some means of detecting double-talk must therefore be implemented. To prevent divergence, the LMS
5 filter coefficients are typically frozen during the presence of double-talk.

Detecting double-talk quickly and reliably is a notoriously difficult problem. Even a small amount of divergence in a fully converged LMS filter will result in a significant increase in the residual echo level. The use of a fast and reliable double-talk detector is crucial to maintain adequate subjective performance.

- 10 The simplest, and perhaps most common, method for detecting double-talk is to use signal levels. The echo path typically contains a minimum amount of loss, or reduction, in the return signal. This quantity is often referred to as the Echo Return Loss, or ERL. In most systems, this is assumed to be at least 6 dB. In other words, the return signal S_{IN} will be at a level which is at least 6 dB lower than R_{OUT} provided that there is no double-talk.
15 In the presence of double-talk, the level at S_{IN} often increases so that it is no longer 6 dB lower than R_{OUT} . This condition provides a simple and convenient test for double-talk.

The problem with this approach is that the double-talk detector must have an accurate estimate of the echo path ERL in order to determine if the level at S_{IN} is too high. However, precise knowledge of the ERL is generally not available. If the ERL estimate is
20 too high, the double-talk detector may trigger unnecessarily. Conversely, it may not trigger at all if the ERL estimate is too low.

Another problem with this technique is that it will only reliably detect high-level double-talk. If the double-talk signal is at a much lower level than the echo source signal, low-level double-talk occurs. Under this condition, the increase in the level of S_{IN} is usually
25 very small. The double-talk detector may fail to trigger, but noticeable divergence in the LMS filter can still occur.

To detect low-level double-talk, the level of the residual echo signal (S_{OUT}) is often monitored. If no double-talk or background noise is present, and the LMS filter is fully converged, S_{OUT} can be as much as 40 dB lower than R_{OUT} . Assuming that the echo path
30 remains constant, any increase in S_{OUT} will likely be due to double-talk. Of course, if the

echo path does change, it will be mistaken for double-talk. So if this method is used, a separate path change detection algorithm must be employed. A unified approach would be simpler and preferred.

Correlation is a statistical function which is commonly used in signal processing. It can provide a measure of the similarity between two signals (cross-correlation), or a single signal and time-shifted versions of itself (autocorrelation). The use of correlation for double-talk detection per se is known. Several patents exist for correlation-based double-talk detection, including US5646990, US5526347 and US5193112. The correlation-based approaches taken in prior-art methods generally involve the calculation of a single cross-correlation coefficient, usually between R_{IN} and S_{IN} . The problem with this technique is that the degree of correlation can vary widely with different signals and echo paths. This makes it very difficult to set thresholds on the correlation coefficient in order to determine what state the echo canceller is in.

SUMMARY OF THE INVENTION

A process has been developed which generates matrix coefficients using zero-lag auto and cross-correlations from signals commonly found in echo cancellers. Double-talk and path changes are then detected using matrix operations such as determinants, eigendecompositions, or singular value decompositions (SVDs).

The correlations between various signals in an echo canceller will change depending on what state the echo canceller is in, i.e. if it is converged, unconverged, or in double-talk. By arranging the various correlations in appropriate matrix form, key information about the state of the echo canceller can be extracted by performing various matrix operations. The preferred operation is to take the determinant, but eigendecompositions and singular value decompositions (SVDs) can also be used. A novel aspect of the invention is the formulation of a matrix using various correlation coefficients, and the subsequent analysis of this matrix to determine the state of the echo canceller.

Accordingly the present invention provides a method of detecting double-talk and path changes in an echo cancellation system, comprising generating a correlation-based matrix of signals in said echo cancellation system; and analyzing said correlation-based matrix to identify double-talk and path changes occurring in said system.

In the preferred embodiment, the correlation-based matrix is generated using the return echo signal (S_{IN}) and the output of an LMS adaptive filter.

The invention provides a correlation-based matrix is generated using zero-lag auto and cross-correlations of signals commonly found in echo cancellers.

- 5 Double-talk and path changes are detected by analysis of the correlation-based matrix. Possible analysis techniques include condition numbers, determinants, eigendecompositions, and singular value decompositions.

In the preferred embodiment, determinants are used to detect double-talk and path changes.

- 10 The invention can be implemented using either the time-domain or frequency-domain in a digital signal processor using conventional digital signal processing techniques.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention will now be described in more detail, by way of example only, with reference to the accompanying drawings, in which;-

- 15 Figure 1 is a schematic diagram of an echo canceller using LMS Adaptive Filtering; and
Figure 2a is a plot showing the value of $\det [R]$ under normal convergence;
Figure 2b is a plot showing the value of $\det [R]$ with a path change; and
Figure 2c is a plot showing the value of $\det [R]$ with double-talk.

DETAILED DESCRIPTION OF THE INVENTION

- 20 The layout of a typical LMS-based echo canceller is shown in Figure 1. It contains two signals, travelling along a "send" path and a "receive" path. The echo source signal enters the echo canceller as R_{IN} and leaves as R_{OUT} . The send path input, S_{IN} , consists of a double-talk signal (if present) plus the echo source signal after it has travelled along the echo path. By estimating the echo path, a synthetic echo signal can be generated to cancel
25 the echo in the send path. The echo cancelled signal leaves as S_{OUT} .

The LMS filter attempts to cancel the echo by adjusting itself to suppress the output signal at S_{OUT} . Obviously, if S_{IN} contains components other than echoed speech from the echo

source, the LMS filter will not converge to the correct solution; hence the need for double-talk detection.

The preferred embodiment of the algorithm for this patent uses the Normalized-LMS (N-LMS) algorithm. Mathematically, the adaptive filter tap-weight update procedure for the

5 N-LMS algorithm consists of the following three equations

$$\hat{d}[n] = \hat{\mathbf{w}}^H[n] \mathbf{u}[n]$$

$$e[n] = d[n] - \hat{d}[n]$$

$$\hat{\mathbf{w}}[n+1] = \hat{\mathbf{w}}[n] + \frac{\mu}{a + \|\mathbf{u}[n]\|^2} \mathbf{u}[n] e[n]$$

where

10 $\mathbf{u}[n] = \mathbf{R}_{IN}$ = echo source signal

$\hat{\mathbf{w}}[n]$ = LMS filter coefficients

$d[n] = \mathbf{S}_{IN}$ = desired LMS output (echo + double-talk)

$\hat{d}[n]$ = LMS output (estimated echo)

$e[n] = \mathbf{S}_{OUT}$ = LMS error signal

15 μ = LMS step-size parameter

a = A small constant (provides numerical stability).

The location of these signals in the echo canceller is also shown in Figure 1. The N-LMS algorithm well known to persons skilled in the art and a more detailed treatment is readily available in most adaptive filtering texts. See, for example, S. Haykin, Adaptive Filter

20 Theory, Prentice-Hall, Upper Saddle River, NJ (1996).

One of the key parameters in the N-LMS algorithm is the LMS step-size parameter μ . This parameter controls both the speed and accuracy of convergence. The larger μ is, the faster the algorithm will converge on the echo path, but the less accurate the steady-state

solution will be. To guarantee convergence of the N-LMS algorithm, μ must be less than 2.

A common technique is to adjust the value of μ based on the state of the echo canceller. In an unconverged state (such as at start-up, or following a path change), it is desirable to use a large value for μ to permit rapid initial convergence. Once the LMS filter has achieved a reasonable degree of convergence, μ can be reduced. This not only allows for a slightly more accurate solution (and therefore more cancellation), but it will also slow potential divergence from double-talk. To stop adaptation altogether, μ can simply be set to zero. The double-talk and path change detectors can therefore control the operation of the LMS filter by varying the value of μ .

A double-talk detection algorithm in accordance with a preferred embodiment of the invention that is designed to work in conjunction with the echo canceller described illustrated in Figure 1 will be described. This is implemented in a digital signal processor.

Consider two signals, $X_0[n]$ and $X_1[n]$ generated by a linear combination of two real-valued source signals, $S_0[n]$ and $S_1[n]$. Mathematically, this mixing process may be described as

$$X_i = H_{i,0} \cdot S_0 + H_{i,1} \cdot S_1, \dots$$

where $H_{i,j}$ are the mixing coefficients. In matrix form, this may be written as

$$\mathbf{X} = \mathbf{H} \cdot \mathbf{S}$$

where

$$\mathbf{X} = \begin{bmatrix} X_0 \\ X_1 \end{bmatrix}, \mathbf{H} = \begin{bmatrix} H_{0,0} & H_{0,1} \\ H_{1,0} & H_{1,1} \end{bmatrix} \text{ and } \mathbf{S} = \begin{bmatrix} S_0 \\ S_1 \end{bmatrix}$$

A matrix \mathbf{R} is defined as

$$\mathbf{R} = E[\mathbf{xx}^T]$$

where $E[\dots]$ is the statistical expectation operator. \mathbf{R} may be expanded in two ways

$$\mathbf{R} = E \begin{bmatrix} X_0 X_0^T & X_0 X_1^T \\ X_1 X_0^T & X_1 X_1^T \end{bmatrix}$$

$$= E [\mathbf{H} \mathbf{S} \mathbf{S}^T \mathbf{H}^T]$$

From the first expansion, it is apparent that the diagonal terms in \mathbf{R} are the zero-lag autocorrelations of $X_0[n]$ and $X_1[n]$ and that both off-diagonal terms correspond to the zero-lag cross-correlation between $X_0[n]$ and $X_1[n]$. Hence, \mathbf{R} is a symmetric, correlation-based matrix.

From the second expansion, we see that if \mathbf{H} is full-rank, then \mathbf{R} will also be full-rank if $S_0[n]$ and $S_1[n]$ are both non-zero and uncorrelated. In most cases, a sufficient condition for this is that $S_0[n]$ and $S_1[n]$ are different signals from different sources.

The way in which the matrix can be used to perform double-talk and path change detection will now be explained. First, suppose we generate the signal mixtures in using convolutions:

$$\mathbf{X} = \mathbf{H} \otimes \mathbf{S}$$

Now the terms in the mixing matrix can be vectors. We further impose the condition that \mathbf{H} have the following form:

$$\mathbf{H} = \begin{bmatrix} H_{0,0} & 1 \\ H_{1,0} & 0 \end{bmatrix}$$

With \mathbf{H} defined in this way, it is now possible to connect the terms in the preceding equations with the parameters available in the echo canceller layout shown in Figure 1.

Let

- 20 S_0 = echo source signal = $R_N = u[n]$
- S_1 = double-talk signal
- $H_{0,0}$ = echo path
- $H_{1,0}$ = LMS filter coefficients = $\hat{\mathbf{w}}[n]$

With these definitions, it is apparent that

$$X_0 = H_{0,0} \otimes S_0 + S_1 = S_N = d[n]$$

$$X_1 = H_{1,0} \otimes S_0 = \hat{d}[n]$$

The question of what happens to \mathbf{R} under the various states of echo canceller operation will now be examined.

5 Case 1: Unconverged, no double-talk

If the LMS filter is in an unconverged state, $H_{0,0} \neq H_{1,0}$. This situation occurs when the echo canceller is first started, or following a major echo path change. Since the LMS filter does not contain an accurate echo path estimate, $X_0 \neq X_1$, and \mathbf{R} will be full rank (unless $H_{1,0} = 0$, but this condition is usually temporary) with a very low condition number. See, for example, G. H. Golub and C. F. Van Loan, Matrix Computations, 3rd ed., Johns Hopkins University Press, Baltimore, MD (1996). ($\kappa \sim 10^1$). As convergence proceeds, the degree of correlation between X_0 and X_1 and increases. This has the effect of rapidly raising the condition number of \mathbf{R} . As a result, the determinant of \mathbf{R} will fall, and its eigenvalues and singular values will become increasingly disparate.

15 Case 2: Converged, no double-talk

In this state $H_{0,0} \approx H_{1,0}$, so $X_0 \approx X_1$. This will make \mathbf{R} very nearly rank deficient, and its condition number very large ($\kappa \sim 10^6$). Since \mathbf{R} is close to being singular, its determinant will become very small. Similarly, we would expect to find only one significant eigenvalue or singular value.

20 Case 3: Double-talk

When double-talk is occurring, X_0 contains components from both S_0 and S_1 , while X_1 is derived solely from S_0 . In this case, X_1 and X_0 are highly uncorrelated. \mathbf{R} will have a low condition number, and this will be sustained for the duration of the double-talk. The higher the double-talk level, the lower the condition number becomes. This will raise the determinant of \mathbf{R} , and we will find two significant eigenvalues and singular values.

Once the matrix \mathbf{R} is generated, a variety of operations are available to determine what state the echo canceller is in. The condition number, determinant, eigenvalues and singular values of \mathbf{R} can all be used to test for double-talk or path changes. The determinant

is used in the preferred embodiment because it is the simplest matrix operation to perform.

To illustrate the effectiveness of this algorithm at detecting double-talk and path changes, simulations were carried out and the results are shown in Figure 2. The plots indicate the value of $\det [\mathbf{R}]$ under normal convergence, a path change, and double-talk. The scaling of the y-axis on the plots clearly demonstrates the variations observed in $\det [\mathbf{R}]$ under the three different states. The simulations were carried out using ITU CSS synthetic speech signals from the G.168 Digital Echo Canceller standard. ITU-T Recommendation G.168, Digital Echo Cancellers. The signals were 48000 samples long, and a 60 ms echo path was used (which was changed to 15 ms during the path change simulation).

Under normal convergence (Fig. 2a), $\det [\mathbf{R}]$ rapidly decays to near-zero values. When a path change occurs (Fig. 2b), $\det [\mathbf{R}]$ spikes to a large value and then decays (to emphasize this trend, convergence was slowed by a factor of 10 following the path change). With double-talk (bottom plot), even larger, but sustained, spikes are present in $\det [\mathbf{R}]$. The differences in these three plots make it very easy to tell what state the echo canceller is in simply by checking the level of $\det [\mathbf{R}]$. The highest levels indicate double-talk, medium levels (along with decay) occurs with path changes, and very low levels are characteristic of full convergence. Based on these results, thresholds can be set as follows:

- Normal (converged) operation.
- Path change detected.
- Double-talk detected.

Once the state of the echo canceller is determined, the LMS filter operation can be adjusted accordingly.

A well-known relation in signal processing is that the convolution of two signals in time is equivalent to the multiplication of their frequency spectra. This property makes it possible to propose a variation on the preceding algorithm in which frequency-domain versions of the signals are used. \mathbf{X} has been defined in the time-domain using convolutions:

$$\mathbf{X}[n] = \mathbf{H}[n] \otimes \mathbf{S}[n]$$

By taking the Fourier Transform of all terms involved, it is possible to rewrite the above equation in the frequency-domain as

$$X(f_k) = H(f_k) \cdot S(f_k)$$

5 for all frequencies in the range $0 \leq f_k \leq F_s/2$ where F_s is the sampling frequency of the signals. The generation and analysis of the correlation-based matrix R is carried out as before, only now R is created using the frequency-domain version of X .

The advantage to this approach is that the algorithm no longer needs to have an accurate echo path estimate for R to have a high condition number during non-double-talk states. The double-talk detector becomes completely insensitive to path changes. Depending on
10 the application, this may or may not be a desirable property. Low-level double-talk detection abilities improve, but a separate path change detection scheme must now be used.

Implementation of a frequency-domain version of this process can be accomplished through the use of Fast Fourier Transforms (FFTs) or subbanding techniques.

15 As will be understood by persons skilled in the art the inventive process can be implemented in a digital signal processor or other suitable digital signal processing device.

Glossary

20 **Adaptive Filter:** A filter whose coefficients can be adjusted during operation. Adaptive filters are used to estimate unknown parameters, for example an unknown echo path.

Autocorrelation: A statistical quantity which roughly measures the similarity of a signal to time shifted versions of itself.

Condition Number: A measure of how close a matrix is to being singular. The condition
25 number for an arbitrary matrix A is given by $\kappa(A) = \|A\| \|A^{-1}\|$.

Convergence: The condition achieved when the LMS filter has accurately modelled the echo path and is no longer undergoing significant changes. At convergence, the LMS filter is cancelling the maximum amount of echo.

5 **Cross-Correlation:** A statistical quantity which roughly measures the similarity of two separate signals.

Divergence: The process by which the LMS filter coefficients move away from the actual echo path to erroneous and unpredictable solutions. During divergence, the amount of echo being cancelled becomes less and less.

10 **Double-Talk:** The condition which occurs during simultaneous transmission of signals from both sides of the echo canceller.

Echo Path: A mathematical description of the process which imparts an echo to a signal.

ERL: Echo Return Loss. The loss a signal experiences as it travels along the echo path from R_{OUT} to S_{IN} .

15 **ERLE:** Echo Return Loss Enhancement. A common method of measuring the performance of an echo canceller. This measurement represents the amount that an echo signal has been reduced from S_{IN} to S_{OUT} .

LMS Algorithm: Least Mean Squares algorithm. Common adaptive filtering technique.

20 **N-LMS Algorithm:** Normalized Least Mean Squares algorithm. A variation on standard LMS in which the tap- weight update term is scaled by the inverse of the input signal power.

Rank: The number of non-zero eigenvalues or singular values a matrix has. Full-rank matrices have a non-zero determinant, and are thus non-singular and invertible.

RLS Algorithm: Recursive Least Squares algorithm. Common adaptive filtering technique.

Claims:

1. A method of detecting double-talk and path changes in an echo cancellation system, comprising:
 - generating a correlation-based matrix of signals in said echo cancellation system;
 - 5 and
 - analyzing said correlation-based matrix to identify double-talk and path changes occurring in said system.
2. A method as claimed in claim 1, wherein said correlation-based matrix is generated using zero-lag auto and cross-correlations of said signals.
- 10 3. A method as claimed in claim 2, wherein a determinant of said matrix is used to detect said double-talk and path changes.
4. A method as claimed in claim 3, wherein said double-talk and path changes are inferred when the value of said determinant passes predetermined threshold values.
5. A method as claimed in claim 2, wherein eigendecompositions of said matrix are
15 used to detect said double-talk and path changes.
6. A method as claimed in claim 2, wherein single valued decompositions of said matrix are used to detect said double-talk and path changes.
7. A method as claimed in claim 2, wherein condition numbers of said matrix are used to detect said double-talk and path changes.
- 20 8. A method as claimed in any one of claims 1 to 7, wherein said echo cancellation system includes an adaptive filter, and said signals comprise an echo signal and an output of said adaptive filter.
9. A method as claimed in claim 7, wherein said filter is an LMS filter.
10. A method as claimed in claim 9, wherein said LMS filter implements a
25 normalized-LMS algorithm.
11. A method as claimed in any one of claims 1 to 10, wherein the elements of said correlation-based matrix are generated in the time domain.

12. A method as claimed in any one of claims 1 to 10, wherein the elements of said correlation-based matrix are generated in the frequency domain.

13. A method as claimed in claim 3, wherein said determinant \mathbf{R} is of the form

$$\mathbf{R} = E \begin{bmatrix} X_0 X_0^T & X_0 X_1^T \\ X_1 X_0^T & X_1 X_1^T \end{bmatrix}$$

5 wherein $X_0[n]$ and $X_1[n]$ are generated by a linear combination of two real-valued source signals, $S_0[n]$ and $S_1[n]$.

14. A method as claimed in claim 1, wherein $S_0[n]$ comprises an echo signal and $S_1[n]$ comprises a cancellation signal.

ABSTRACT OF THE DISCLOSURE

A process is described which generates matrix coefficients using zero-lag auto and cross-correlations from signals commonly found in echo cancellers. Double-talk and path changes are then detected using matrix operations such as determinants, eigendecompositions, or singular value decompositions (SVDs). In a preferred embodiment, the determinant of the correlation-based matrix is compared against predetermined threshold values.




Figure 1

Inis Page Blank (uspto)




Fig. 2a




Fig. 2b




Fig. 2c

This Page Blank (uspto)